

# Configurations

## List API

### HTTP REQUEST: GET

Get the list of all Configurations at the Organization scope.

```
GET /api/1.0/org/{orgId}/properties/configurations
```

#### URI PARAMETERS

Name	Type	Description
orgId	string	The Organization ID (UUID) for which you are querying.

#### RESPONSES

Code	Description
200	Success.
401	This error will occur if calling user does not have access right for the API.
404	This error will occur if the org identified by orgId does not exist.
500	A server error occurred. Check the logs for more details.

200 Reponse Body

```
{  
  "status": {  
    "i18n_message": "response.ok",  
    "message": "OK"  
  },  
  "response": [  
    {  
      "id": "account.host",
```

```
    "name": "account.host",
    "value": "local.infra.atscale.com",
    "type": "string",
    "role": "configuration",
    "group": "account",
    "configurable": true,
    "scope": "global"
  },
  {
    "id": "account.port",
    "name": "account.port",
    "value": "10500",
    "type": "int",
    "role": "configuration",
    "group": "account",
    "configurable": true,
    "scope": "global"
  },
  {
    "id": "modeler.host",
    "name": "modeler.host",
    "value": "local.infra.atscale.com",
    "type": "string",
    "role": "configuration",
    "group": "design center",
    "configurable": true,
    "scope": "global"
  },
  {
    "id": "tableau.server.readTimeout",
    "name": "tableau.server.readTimeout",
    "value": "60s",
    "type": "int",
    "role": "configuration",
    "group": "tableau",
    "configurable": true,
    "scope": "global"
  }
]
}
```

# Update API

## HTTP REQUEST: POST

Set the Configuration value for an Organization scoped Configuration

```
POST /api/1.0/org/{orgId}/properties/configurations/update
```

### URI PARAMETERS

Name	Type	Description
orgId	string	The Organization ID (UUID) where you make updates

### QUERY PARAMETERS

Name	Type	Description
name	string	Name of the configuration
value	string	New value of the configuration

### RESPONSES

Code	Description
200	Success.
401	This error will occur if calling user does not have access right for the API.
404	This error will occur if the org identified by orgId does not exist.
500	A server error occurred. Check the logs for more details.

Request Body

```
{
  "name": "session.timeout",
  "value": "3h"
}
```

200 Reponse Body

```
{
  "status": {
    "i18n_message": "response.ok",
    "message": "OK"
  },
  "response": "3h"
}
```

## Organization Override API

### HTTP REQUEST: PUT

Create a new Organization Scoped Configuration with the value passed in.

```
PUT /api/1.0/org/{orgId}/properties/configurations/{globalConfigurationId}/{value}
```

#### URI PARAMETERS

Name	Type	Description
orgId	string	The Organization ID (UUID) for which you are querying.
globalConfigurationId	string	The Global Scope Configuration ID (non-UUID, human readable) for which you are querying.
value	string	The Value you want to set the configuration to

#### RESPONSES

Code	Description
200	Success.
401	This error will occur if calling user does not have access right for the API.

404	This error will occur if the org identified by orgId does not exist.
500	A server error occurred. Check the logs for more details.

## 200 Reponse Body

```
{  
  "status": {  
    "i18n_message": "response.ok",  
    "message": "OK"  
  },  
  "response": {  
    "id": "account.host",  
    "name": "account.host",  
    "value": "value",  
    "type": "string",  
    "role": "configuration",  
    "group": "account",  
    "configurable": true,  
    "scope": "local"  
  }  
}
```